

Bodine BSL23 LED Emergency Driver



Bodine BSL23 LED Emergency Driver. The BSL23 emergency LED driver works in conjunction with an AC LED driver that has an output current not to exceed 1.5 A, convert new or existing LED fixtures into emergency lighting. The emergency driver consists of a high-temperature nickel-cadmium battery, charger and electronic circuitry in one compact red case.

Benefits:

Emergency Illumination for Lower Wattage LED fixtures

For Indoor or Damp Locations

Specifications

UL Component Recognized For Factory Installation only (Indoor and Damp)

Illumination Time 90 Minutes

Full Warranty 5 Years (NOT pro-rata)

Dual Input Voltage 120/277 VAC, 60 Hz

AC Input Current 280 mA

AC Input Power Rating 2.0 W

Output Voltage 3.0 to 20.0 VDC

Output Current 410 mA (Maximum)

Output Power 4.5 W (Maximum)

Test Switch/Charging Indicator Light Illuminated Test Switch

Battery High-Temperature, Maintenance-Free Nickel-Cadmium
Battery 7- to 10-Year Life Expectancy

Battery Charging Current 250 mA

Recharge Time 24 Hours

Temperature Rating (Ambient) 0°C to +50°C (32°F to 122°F)

Dimensions 9.4" x 2.4" x 1.5" (238 mm x 60 mm x 38 mm)
Mounting Center 8.9" (226 mm)

Weight BSL23 – 1.8 lbs. (0.82 kg)

For other items like the Bodine BSL23 LED Emergency Driver 4.5
Watts Output Power [click here](#).

For more information on Bodine's line of lighting solutions
[click here](#).