

# Bodine LP600 Fluorescent Emergency Ballast



Bodine LP600 Fluorescent Emergency Ballast. Low-Profile for Space-Limited Fixtures, standard and H0 T5 and T8 Lamps. End-of-Lamp-Life Compatible. The LP600 low-profile emergency ballast works in conjunction with a low-profile or standard-size AC ballast to convert new or existing standard or high-output T5 and T8 fluorescent fixtures into unobtrusive emergency lighting. The emergency ballast consists of a high-temperature nickelcadmium battery, charger and electronic circuitry in one compact case

## Benefits

- Low Profile case
- Emergency mode lumen output up to 1325 lumens
- End-of-Lamp-Life Compatible
- Compatible with TLED lamps (see Table 1)

## Specifications

UL Listed for US and Canada

Listed to UL924 and tested to CSA 22.2 No. 141

Field or Factory Installation (Indoor and Damp) Output Class 2 Compliant

Illumination Time

90 Minutes

Initial Light Output

600 – 1325 Lumens @ 25°C

Full Warranty

5 Years (NOT pro-rata)

Dual Input Voltage

120/277 VAC, 60 Hz

AC Input Current

180 mA

AC Input Power Rating

3.0 Watts

Test Switch

Single Pole

Battery

High-Temperature, Maintenance-Free

Nickel-Cadmium Battery

7- to 10-Year Life Expectancy

Battery Charging Current

165 mA

Recharge Time

24 Hours

Charging Indicator Light

LED

Temperature Rating (Ambient)

0°C to +50°C (32°F to 122°F)

Dimensions

21.5" L x 1.18" W x 1.18" H

(546 mm x 30 mm x 30 mm)

Mounting Center 21.1" (536 mm)

Weight

3.3 lbs. (1.5 kg)

For other items like the Bodine LP600 Fluorescent Emergency Ballast [click here](#).

For more information on Bodine's line of lighting solutions [click here](#).