

Bodine B70A Emergency Ballast



Bodine B70A Emergency Ballast. The B70A emergency ballast works in conjunction with an AC ballast to convert new or existing fluorescent fixtures into emergency lighting.

The emergency ballast consists of a high-temperature nickel cadmium battery, charger and electronic circuitry in one compact red case. For damp locations; Two-hour emergency illumination; End-of-lamp-life-compatible.

For damp locations; Two-hour emergency illumination;
End-of-lamp-life compatible

UL Listed

Factory or Field Installation (Damp)

Illumination Time

90 Minutes (Standard) or
120 minutes

(One 17-32 W T8, One 20-40 W T10 or T12)

Initial Light Output

600 – 700 Lumens

Full Warranty

3 Years (NOT pro-rata)

Voltage

120/277 VAC, 60 Hz

AC Input Current

280 mA

AC Input Power Rating

3.5 Watts

Test Switch

Single Pole

Battery

High-Temperature, Maintenance-Free

Nickel-Cadmium Battery

7- to 10-Year Life Expectancy

Battery Charging Current

280 mA

Recharge Time

24 Hour

Charging Indicator Light

LED

Temperature Rating (Ambient)

Damp Location

0°C to +50°C

(32°F to 122°F)

Dry Location

0°C to +55°C

(32°F to 131°F)

Dimensions

9.4" x 2.4" x 1.5"

(238 mm x 60 mm x 38 mm)

Mounting Center 8.9" (226 mm)

Weight

2.5 lbs. (1.13 kg)

Model B70A is warranted for three (3) full years from date of purchase. Please see detailed warranty information on the

Signify official website.

For other items like the Bodine B70A Emergency Ballast click here.

For more information on Bodine's line of lighting solutions click here.