

# Bodine Ballast

# B94GU

# Emergency



Bodine B94GU Emergency Ballast. The B94GU emergency ballast works in conjunction with an AC ballast to convert new or existing fluorescent fixtures into emergency lighting. The emergency ballast consists of a high-temperature nickel-cadmium battery, charger and electronic circuitry in one compact case. Universal input voltage; One-lamp emergency illumination for 4-pin fluorescent lamps (without integral starter); Suitable for low mercury lamps.

UL Listed for US and Canada  
Factory or Field Installation  
(Indoor and Damp)

Illumination Time  
90 Minutes

Initial Light Output  
300 – 750 Lumens

Full Warranty  
2 Years (NOT pro-rata)

Universal Input Voltage  
120 Through 277 VAC, 50 or 60 Hz

AC Input Current  
50 mA

AC Input Power Rating

4.0 Watts

Test Switch

Single Pole

Battery

High-Temperature, Maintenance-Free

Nickel-Cadmium Battery

7- to 10-Year Life Expectancy

Battery Charging Current

300 mA

Recharge Time

24 Hour

Charging Indicator Light

LED

Temperature Rating (Ambient)

0°C to + 50°C (32°F to 122°F)

Dimensions

9.4" x 2.4" x 1.5"

(238 mm x 60 mm x 38 mm)

Mounting Center 8.9" (226 mm)

Weight

3 lbs. (1.4 kg)

Model B94GU is warranted for two (2) full years from date of purchase. Please see detailed warranty information on the Signify official website.

For other items like the Bodine B94GU Emergency Ballast click [here](#).

For more information on Bodine's line of lighting solutions click [here](#).