

CS-50 – PIR WALL SWITCH VACANCY SENSOR



This is the PIR wall switch vacancy sensor. The CS-50 Passive Infrared (PIR) Vacancy Sensor provides automatic shutoff for single-pole lighting control applications. It is engineered to comply with specific provisions of California's Title 24-2013 energy code. The CS-50 operates as a manual-on sensor. Users must press the pushbutton to turn on lighting. The CS-50 employs PIR technology to sense the difference between the infrared energy from a person in motion and the background space. It keeps lighting on as long as motion is detected and provides automatic shutoff, following a user-selected time delay, when motion is no longer detected. Users may turn the lighting off manually. The CS-50 is shipped preset for a 30 minute time delay, and does not require any adjustment after installation. If desired, the time delay may be easily reduced to 25, 20, 15, 10 or 5 minutes or to 30 seconds. The time delay should be set relative to the anticipated duration of stay and level of activity in the room; 30 minutes for guest room and executive restroom, and 5 to 10 minutes for pantries and laundry rooms. **Check out Wattstopper DLM products here.**

- Replaces single-pole switches
- Adjustable time delay, 30 seconds to 30 minutes
- If enabled, status indicator blinks when motion is detected
- Low-profile styling
- Choice of five decorator colors; lens is color-matched to device

- Operates most common types of lighting or fan motors
- Relay-based switching
- No current leakage to load in off mode for safety
- Compatible with decorator wall plates
- CA Title 24 compliant